

UHF2390
2 WATT
UHF CB
RADIO
TWIN PACK



3 YEAR WARRANTY

 **oricom**[®]
100% AUSSIE OWNED

UHF2390

2 WATT UHF

CB RADIO

TWIN PACK

This 2 Watt UHF CB radio twin pack features a LED torch, dual watch and a vibrant backlit display. Whether you're off road, camping, fishing or working around the construction site, this UHF CB radio twin pack is the perfect way to keep in touch.

KEY FEATURES

- 2 watt transmit power
- LED torch
- 80 Channels
- Duplex (range extender)
- 38 CTCSS & 83 DCS codes
- Backlit display
- Dual watch
- Roger beep
- Channel scan
- Automatic squelch control
- Keypad lock
- Hands-free (VOX) capable
- Call tone alert
- 3 Year warranty

3 YEAR WARRANTY

oricom.com.au

Oricom® is the registered trademark of Oricom International Pty Ltd.



TECHNICAL SPECIFICATION

GENERAL

Compliance	AS/NZS 4365:2011 and NZS2772.1
Frequency Range TX/RX	476.425 - 477.4125 MHz
Number of Channels	80 UHF CB (75 Usable)†
Channel Spacing TX/RX	12.5KHz
Channel Spacing RX	12.5KHz
Operating modes	Simplex, Duplex
Battery Capacity	4 x AAA Ni-MH 600mAh batteries. 10 hours operating time using low power. Duty cycle; 5% transmit, 5% receive and 90% standby.
Frequency Stability	+/- 2.5ppm

Transmitter

RF Output Power	2 Watts max.
Modulation	FM
Maximum Deviation	+/- 2.5KHz
Tx Frequency Response	+1 to -3dB of 6dB/octave from 300Hz to 3000Hz
Audio Signal to Noise Ratio	more than 30dB

Receiver

Circuit Type	Direct conversion by Single DSP chip
Intermediate Frequencies	IF = 137KHz
Sensitivity	Less than -118dBm at 12dB SINAD
Intermodulation Immunity	more than 70dB
Spurious Response Immunity	more than 60dB
Audio Signal to Noise Ratio	More than 30dB
Receive Frequency Response	5.5 to -9.9 +/-2.5dB from 300Hz to 2500Hz

PACK INCLUDES

- 2 x UHF CB radios
- 1 x Twin charging pod
- 1 x AC Adaptor
- 8 x Rechargeable batteries
- 2 x Belt clips

 **oricom**[®]
100% AUSSIE OWNED